




# DJ-VX50 Firmware upgrade Instructions.

1. Install  DJ-VX50H Update\_V1.23setup.exe
2. Run "DJ-VX50HT Upgrade" in "Administrator mode"
  - (Place the Mouse cursor on "DJ-VX50HT Upgrade" icon and Right click the Mouse button)  
Select "**Properties**" and click on "**Compatibility**" Check on "**Run this program as an Administrator**"
3. Plug in the Alinco USB Data Cable ERW-7 or ERW-15 to your PC and radio. (Make sure to check the "COM Port" Number assigned to the cable in your PC's Device manager settings). Power on the radio.
4. Run "DJ-VX50THT Upgrade" Select COM Port assigned to the Data cables
5. If you get an error "**MSCOMM32.OCX**", please copy this file included with the firmware to your PC "**C:/Program Files/DJ-VX50HT Upgrade**" folder and run the program again.
6. Select "**Upgrade**" and this should initiate the Upgrade process.



7. Check the firmware version
  - Press FUNC then press and hold "#"key until radio keypad is locked.
  - Press the "ESC" key 5 times. The LCD will display the version is 1.23



8. Remember to unlock the keypad after finish (press FUNC then press and hold "#"key to unlock keypad)
9. If you would like to reset radio to factory default setting status just press,
  - Press and hold "PF2" key + PTT key and turn on the Radios
  - Let go of the keys. You will see "DSP" Freq.
  - Press arrow "Up" Key and you will see "RESET"
  - Turn the main dial knob to "FACT" and hit "FUNC" key
  - Enter "000000" (6 digits) and the unit will perform RESET